


Installation

Please follow the steps below to install the 3D Sticker Plugin on your LightWave 3D.

Step 1: Putting the plugin file directly into the plugins folder

Copy the “**3DSticker.p**” (“**3DSticker.plugin**” under Macintosh OS X) file into your plugins directory and launch Modeler.




Step 2: Adding the plugin into LightWave

NOTE: When the **Autoscan Plugins** option is checked (enabled by default) on the General Options Panel, and if the plugin file is placed under LightWave’s plugins directory (located under \LightWave_< VERSION NUMBER > by default), it will be automatically added into LightWave, therefore you will be able to skip this step.


Choose **Utilities > Plugins: Add Plugins** to add the plugin into LightWave. Immediately after selecting the “**3DSticker.p**” file, the Add Plugins Panel appears, which should report back that the following plugin has been added.

- 3PS_3DSticker




Step 3: Adding the button into the Toolbar menu

Choose **Edit > Edit Menu Layout** to open the Configure Menus Panel. In the Menus window, right click at the place where you want to place the button, and choose “**Import Branch**” from the list, then selecting the “**3DSticker_menu.cfg**” file will add the 3D Sticker button into the Tool menu.




If that does not give you the expected result, try manually adding the button into the Tool menu. Choose **Additional > 3PS_3DSticker** in the Command list on the left, and select your target location in the Menus list on the right, then click the **Add** button.



Registration

Please register and activate your plugin. Before your plugin registration and activation are complete, clicking on the **3D Sticker** button will open the 3rd Powers Plug-ins Panel. This panel shows your serial number and allows you to activate your plugin by selecting a license key file.



This is a unique number for tying the plugins to LightWave. All the 3rd Powers Plugins generate the same number for the same LightWave license. Please open the "RegistrationForm.txt" file and enter the list of Serial Numbers and Product Names while referring to the following examples, then send it to "**register@3rdpowers.com**". After that, we will send you the LICENSE KEY file necessary for activation.

This does not mean that you can only use the plugin on a registered machine. The license of our plugins is based on LightWave's. The license key of our plugins is linked to LightWave's license (or dongle). Because it is not locked to a machine, you can install them on both your Mac and PC, desktop and laptop also, and also network rendering is free. Even if you upgrade your copy of LightWave, your license code will be unchanged, therefore you will be able to continue using your current LICENSE KEY file without applying for re-issue of LICENSE KEY file.

Example 1:

If you purchased three “Special Pack GO 2014” licenses to use them on three machines (copies of LightWave), named A, B, and C, the following would be an example of the Registration Form entry.



Example 2:

If you purchased two “Meta Mesh”, two “Lattice Deformer”, and two “Cage Deformer” licenses to use the Meta Mesh and Lattice Deformer plugins on the machine A and B, and to use the Cage Deformer plugins on the machine B and C, the following would be an example of the Registration Form entry. In this example, two forms are needed.


Registration Form 1	Registration Form 2
Product Name: 1: Meta Mesh 2: Lattice Deformer	Product Name: 1: Cage Deformer
Serial Number: 1: AA-AAAA-AAAA 2: BB-BBBB-BBBB	Serial Number: 1: BB-BBBB-BBBB 2: CC-CCCC-CCCC

Activating your plugin with the LICENSE3PS.KEY file

To activate your plugin, please apply your LICENSE3PS.KEY file to the plugin in one of the following ways:

(1) Loading your LICENSE3PS.KEY file on the Serial Number Panel

After opening the unregistered 3D Sticker tool, click the **License File** button on the Serial Number Panel, and then select your LICENSE3PS.KEY file and make sure that its file path is shown in the text field. Finally, click the **Continue** button to close the panel. If a “Product activation successful” message appears, your plugin will be ready.



(2) Copying your LICENSE3PS.KEY file directly into LightWave Setting directory

Copy the LICENSE3PS.KEY file into LightWave Setting directory (Default is as below), and you'll be finished with the process for activation.

If you use the custom Setting directory or multiple versions of LightWave, you will have to copy your LICENSE3PS.KEY file into each Setting directory.

Windows XP

9.6 "C:\Documents and Settings\{USERNAME}"
10.0 and higher "C:\Documents and Settings\{USERNAME}\.NewTek\LightWave\{VERSION NUMBER}"

Windows Vista, 7, 8

9.6 "C:\Users\{USERNAME}"
10.0 and higher "C:\Users\{USERNAME}\.NewTek\LightWave\{VERSION NUMBER}"

Macintosh

9.6 "/Users/{USERNAME}/Library/Preferences/LightWave3D"
10.0 and higher "/Users/{USERNAME}/Library/Application Support/NewTek/LightWave/{VERSION NUMBER}"

NOTE: If you are using LightWave on a Mac using OSX 10.7 or higher, in the Finder, hold down the Alt(Option) key when using the Go menu, and the user library folder to access your library folder appears.

Serial Number: AA-AAAA-AAAA




SN_AA_AAAA_AAAA


LICENSE3PS.KEY

Windows

for LightWave 9.6




for LightWave 10.0 and higher



Macintosh

for LightWave 9.6



for LightWave 10.0 and higher

